



Proximity Credential Order Form

PIVKey C70 Series 125 kHz Proximity Card (PACS) Programming Information

Taglio C70 cards are based on the Identiv uTrust Proximity Technology Card. The physical access control formats that are supported are shown in the table below.

Note: If you are not sure about your programming, please contact Taglio to discuss your order. We can work with you to ensure the programming is correct.

Company Name _____

PO # (if known) _____

Format Code _____(26D - H10301)

Facility Code _____(example: 100)

Card Start Number _____(example: 10100)

Quantity _____

I acknowledge that the programming configuration I have selected makes these cards custom products and as such they are not returnable and makes this sale non-refundable.

Date _____

Signature _____

PLEASE EMAIL COMPLETED FORM TO SALES@TAGLIO.COM

Technical data is subject to change without notice.
Revision/Date of Release: 2021-09-01

Office: 508 East 53rd Street #101, Austin, TX, 78751, United States

Supported Physical Access Control System (PACS) Formats

Identiv Format	Format Code	Issuer	Bits	Possible Facility Codes		Possible Card Serial Numbers	Notes
26AD	AWID	AWID	26	0 – 255		0 – 65,535	
26A 26D	H10301	General Distribution	26	0 – 255		0 – 65,535	
26DMP	D12200	Digital Monitoring Products (DMP)	26	0 - 127		0 - 131,071	FC is 7 bits long, card number 17 bits
26I 26ID	40134	Indala (E/O Parity)	26	0 – 255		0 – 65,535	
26IF	41106	Indala (E/E Parity)	26	0 – 255		0 – 65,535	
26IG		Indala (O/O Parity)	26	0 – 255		0 – 65,535	
27B	P3BSB27	BSB Electronics	27	0 - 8191		0 - 16,383	
32D			32	0 - 16,383		0 - 65,535	
32E	I11201	Intercon Security Limited	32	0-8,191		0-32,767	
32H 32Q	Quadrakey	Honeywell	32	n/a		0 – 4,294,967,295	
33D	D10202	DSX	33	Default 17		0 – 16,777,215	Default FC 17
34A	A14001		34	0 – 255		0 – 1,048,575	
34B	i909482A		34	0 – 127		0 – 131,071	
34C 34S	C10001	Requires Issue Code (0-7)*	34	0 – 7*	0 – 8,191	0 – 65,535	
34D	H10306		34	0 – 65,535		0 – 65,535	
34E 34N	N10002	Honeywell (Northern)	34	0 – 65,535		0 – 65,535	
34F 34G	I10001	Geoffrey/Schlage	34	0 – 4,095		0 – 1,048,575	
34J	JCI	Requires Issue Code	34	0 – 7*	0 – 65,535	0 – 65,535	
35D	H5XXXX	Corp1000	35	0 – 4,095		0 – 1,048,575	
35E	H5XXXX		35	0 – 8,191		0 – 1,048,575	
36B	C15001	Keyscan	36	0 – 255		0 – 65,535	
36C	C10202	Continental (A17601)	36	0 – 65,535		0 – 65,535	
36D	S12906	Simplex	36	Default 217		0 – 16,777,215	Default FC 217
36E	L11601	Lenel	36	0 – 1,023		0 – 262,143	
36I	i10601		36	0 – 8,191		0 – 131,071	
36J	N901157A	Napco	36	0 – 255		0 – 67,108,863	
36M	H10313M	HID 36 9 Digit ID Code + Facility Code (36 bits)	36	0-15		0-1,073,741,823	
36S	S10601		36	0 – 16,383		0 – 1,048,575	
37A	A10202		37	0 – 4,095		0 – 524,287	
37C	S10701		37	0 – 1,023		0 – 65,535	
37D 37H	H10302	HID 37 No FC	37	n/a		0-34,359,738,367 (limited to 4,294,967,295 in Identiv encoder)	
37E 37X	H10304	HID 37 with FC	37	0 – 65,535		0 – 524,287	
37G	S10401	AMAG	37	Default 9		0 – 536,870,911	Default FC 9
37I	I10304		37	0-63		0 – 65,535	
40C	C10106	GE – CasiRusco	40	Up to 12 digit number, must begin with "15"		0 – 457,681	
				151,552 – 155,632			
				Example: 155632 457681			
40D	H10314		40	0 – 4,095		0 – 65,535	
48A	Corp"2000"	New Corp1000 format	48	0 – 4,194,303		0 – 8,388,607	
64K	Kantech XSF	Requires Extended Family Code & Family Code	64	Ext. Fam: Must Provide		0 – 65,535	

Other formats are available on demand or can be developed.

If you have any questions or a format you have is not listed, please inquire with customerservice@identiv.com